

LOCAL PAGING SYSTEMS

PA-4 Series

MULTIPLE BASE TO SINGLE PAGERS

- PA4-TX Transmitter
- PA4-RX Pager
- PA4-RPT Repeater
- PA6-Splitter

Table-top/wall-mounted Transmitter
Beeping/Vibrating Pager with LCD Display
Repeater Transceivers to extend range
Multiple Charging Splitter

Press the left hand button on the Transmitter or activate the built-in trigger input and the Pager/s coded to that Transmitter will start to beep and vibrate. The LCD screen at the top of the Pager displays the Transmitter Number

Applications:

- Warehouses, Factories, Offices
- Nursing Homes
- Supermarkets, Shops, Sports Complexes
- Hotels, Restaurant, Pubs, Kitchen

Features:

- 433 MHz – ETSI 300/220
- Extend range using repeaters
- Pager has an 8 event memory
- Each Transmitter is coded to one of 99 channels
- Push Button activation or connect to any NC or NO external device
- Each Transmitter will transmit to one or more Pagers
- Transmitters can be divided into 4 separate groups
- Transmitter uses alkaline batteries – Pager uses rechargeable batteries



Technical Specifications:

Colour: Black (Transmitter)
Black (Pager)
White (Repeater)

Power Supply:

PA4-TX 4 x AAA Alkaline Batteries
PA4-RX 9V Rechargeable Battery
PA4-RPT 12DC Adaptor (9V Battery back-up)

Range: 30-70 Metres depending on environment. Extend range using up to 5 repeaters per system.

Current Consumption:

PA4-T > 0.1mA
PA4-R > 6mA
PA4-RPT > 10mA

Dimensions:

PA4-T 110 x 70 x 30 mm
PA4-R 80 x 55 x 22 mm
PA-RPT 100 x 75 x 30 mm

Model	Description
PA4-T	Desktop Transmitter complete 4 x AAA batteries
PA4-R	Pager Receiver complete with 9V rechargeable battery and mains charger
PA4-RPT	Repeater Transceiver complete with 12V adaptor
PA6-SPLITTER	Electronic Splitter for use with PA4-R charger. Connects to 5 Pagers



Keystone Electronics Limited
Winfrith Technology Centre, Winfrith Newburgh, Dorchester, Dorset DT2 8ZB
Tel: +44 (01305) 853090 Fax: +44 (01305) 851660
Email: sales@keystone-electronics.co.uk Website: www.keystone-electronics.co.uk